

# **IRG 400 portable**

**BAUR time domain reflectometer** 



The figure is illustrative.

# **Reliable and fast cable fault location**

- Precise pre-location with high-performance technology
- Light, compact and portable
- Maximum safety for operators
- Can be installed in cable fault location systems

The IRG 400 portable time domain reflectometer is used for fault pre-location on single- and multi-phase cables. The integrated separation filter allows TDR measurements to be performed on live cables up to measurement category CAT IV/600 V.

Thanks to the intuitive operational concept, cable faults can be located more rapidly and easily with the IRG 400 portable. Using the IRG 400 portable and the BAUR BUI-F application, TDR fingerprints of cables can be created that allow comparisons against existing reference measurements. Changes in the cable can therefore be detected immediately. The recorded measurement results can be exported via the tablet's USB interface and imported into the BAUR Software 4 for further processing, e.g. reporting.

The measuring device and tablet are connected via Wi-Fi. Therefore the measurement can be controlled and traced safely and conveniently using the tablet outside of the danger zone.

## Functions

- TDR: time domain reflectometry (1- and multi-phase)
- Step TDR for the pre-location of cable faults and joints in the vicinity (1- and multi-phase)
- In combination with BAUR surge voltage generators
  - SIM/MIM: secondary/multiple impulse method
  - DC-SIM/MIM: secondary/multiple impulse method used in DC mode
  - ICM: impulse current method
  - DC-ICM: impulse current method used in DC mode
- In combination with BAUR HV generators with DC voltage
  - Decay method (option)

#### Features

- Intuitive user interface in multiple languages
- Measurement controlled via a tablet using the BAUR BUI-F application
- Length-dependent gain for better display of remote events
- Greater convenience, as measurements can be controlled via Wi-Fi
- Integrated separation filter (can be enabled/disabled) for TDR measurements on live cables with measurement category CAT IV/600 V
- Everything needed for the measurement in one handy case – time domain reflectometer, tablet, accessories
- Suitable for use in the field and weatherproof (splash water and dust protection)
- Operation via rechargeable battery or mains voltage



### **Technical data**

IRG 400 portable	
Pulse voltage	60 V
Pulse width	30 ns – 10 μs
Voltage-proof up to	400 V, 50/60 Hz
Measurement category	CAT IV/600 V (with enabled separation filter)
Input signal gain	Dynamic range 101 dB (-63 to +38 dB)
Display range	10 m – 1,000 km
Accuracy	0.1% (relating to the measurement result)
Data rate	400 MHz
Resolution	0.1 m (at v/2 = 80 m/µs)
Velocity of propagation (v/2)	20 – 150 m/µs, adjustable
Control of measurements	BAUR BUI-F application, installed on a tablet
Power supply	
Mains voltage	100 – 240 V, 50/60 Hz
Rechargeable battery	Lithium-ion battery, 14.4 V
external DC power supply	12 – 24 V, 65 W
Battery life	Approx. 6 h
Battery charging time	Approx. 4 h

Dimensions	Approx. 371 x 259 x 152 mm
Weight	<ul> <li>IRG 400 portable (acc. to standard delivery): approx. 7.7 kg</li> </ul>
	<ul> <li>Tablet: approx. 1.1 kg</li> </ul>
Degree of protection	IP54
Ambient temperature (operational)	-20°C to +55°C
Storage temperature	-20°C to +65°C
Safety and EMC	CE-compliant in accordance with Low Voltage Directive (2014/35/EU), EMC Directive (2014/30/EU), EN 60068-2-ff Environmental testing
SCORPION industrial tak	plet
Operating system	Windows 11
Degree of protection	IP65
	<ul> <li>MIL-STD-810G</li> </ul>
Rechargeable battery	Lithium-ion battery, 7.6 V, 5,000 mAh

#### **Standard delivery**

- IRG 400 portable time domain reflectometer, incl.:
  - TDR connection cable, 2 m, with connection clips and fuses
  - BNC cabel 2 m
  - BNC adapter, 2 x connection Ø 4 mm
  - Connection cables, red and black, 0.75 m each, with fuses
  - Earth cable, 3 m, with earth terminal
  - Charger incl. country-specific adapter
  - User manual
- SCORPION industrial tablet, incl.:
  - Windows operating system
  - BAUR BUI-F application for cable fault location
  - Main charger

Information on individual functions and the required accessories can be obtained from your BAUR representative.

#### **Accessories and options**

- Holder for IRG 400 portable
- BAUR Software 4 for office PC (office installation)



